

Smart Operational Panel SOP G2 OS Readme

Smart Operational Panel System Version Update

This needs to be updated from the zip file to an SDcard by loading the zip file on the root directory of a blank SDcard. (card must be 128Mb to 1Gb)

The machine MUST BE powered off before inserting card.

SDcard needs to be installed in the Smart Operational Panel slot.

1. Enter user setting and make sure Screen Start Up mode is set as "Normal".
Note: To change above setting,
Enter User Tools > Screen Features > Screen Device Settings > Screen Start Up mode.

2. Power OFF main switch

Note: EX1 button is the uppermost bottom. EX2 button is the middle button. EX3 button is the lower button.

3. Remove the small cover from left side of the Smart Operation Panel.
4. Turn ON main switch while holding down EX1 and EX3 key together.
5. When the blue splash screen appears, release the buttons, then press EX1 and EX2 key. The panel enters into the recovery mode.
6. Press EX2 key to highlight "apply update from SDcard"
7. Press the EX3 to select
8. Press EX2 key to highlight the ".....zip" file
9. Press the EX3 to select
10. Verify version and press EX1 key to continue update
11. When it displays "Cache wipe complete", select reboot system now.

Untitled

Smart Operational Panel APP Update

IMPORTANT NOTE: 5DKSERVICE APP MUST BE INSTALLED BEFORE WEB BROWSER NX.
IF YOU ARE LOADING WEB BROWSER NX APP BE SURE THIS IS DONE LAST OF ALL THE APPS.

This needs to be updated from an SDcard by loading the zip file with the .apk and .dalp extensions in the app folder on root directory. (Card must be 12Mb to 1Gb)

SDcard needs to be installed in the Smart Operation Panel slot.

Press the "Reset" button -> 8,0,6,1,8,3,#,# -> Press and Hold the "Clear" button for more than 3 seconds.

Select Application --> Install --> Install from the SD Card and start installation
Select the application to be updated and select Install.
The version update result is displayed.

Follow the instruction from the Smart Operational Panel System Maintenance section
4.1.4 Application Installation/version update.

Important Note: All apps are model specific. certain apps belongs only to printer models.